

Measuring class parameter [Floating point format data]

Input Register Parameter [Function code : 04H]				Register Address [Hex]	
Description	Length (bytes)	Data Format	Units	High Byte	Low Byte
Phase 1 line to neutral volts.	4	Float	V	00	00
Phase 2 line to neutral volts.	4	Float	V	00	02
Phase 3 line to neutral volts.	4	Float	V	00	04
Phase 1 current.	4	Float	A	00	06
Phase 2 current.	4	Float	A	00	08
Phase 3 current.	4	Float	A	00	0A
Phase 1 active power.	4	Float	W	00	0C
Phase 2 active power.	4	Float	W	00	0E
Phase 3 active power.	4	Float	W	00	10
Phase 1 reactive power.	4	Float	var	00	12
Phase 2 reactive power.	4	Float	var	00	14
Phase 3 reactive power.	4	Float	var	00	16
Phase 1 apparent power.	4	Float	VA	00	18
Phase 2 apparent power.	4	Float	VA	00	1A
Phase 3 apparent power.	4	Float	VA	00	1C
Phase 1 power factor (1).	4	Float	None	00	1E
Phase 2 power factor (1).	4	Float	None	00	20
Phase 3 power factor (1).	4	Float	None	00	22
Phase 1 phase angle.	4	Float	Degrees	00	24
Phase 2 phase angle.	4	Float	Degrees	00	26
Phase 3 phase angle.	4	Float	Degrees	00	28
Line 1 to Line 2 volts.	4	Float	V	00	2A
Line 2 to Line 3 volts.	4	Float	V	00	2C
Line 3 to Line 1 volts.	4	Float	V	00	2E
Frequency of supply voltages.	4	Float	Hz	00	30
Total system active power.	4	Float	W	00	32
Total system reactive power.	4	Float	var	00	34
Total system apparent power.	4	Float	VA	00	36
Total system power factor (1).	4	Float	None	00	38
Total system phase angle.	4	Float	Degrees	00	3A
Sum of line currents.	4	Float	A	00	3C
Average line to neutral volts.	4	Float	V	00	3E
Average line to line volts.	4	Float	V	00	40
Average line current.	4	Float	A	00	42
Neutral current.	4	Float	A	00	44
Nature of L1 load (Resistive=1, inductive=2, capacitive=3, Non Load=4)	4	Float	None	00	4E
Nature of L2 load (Resistive=1, inductive=2, capacitive=3, Non Load=4)	4	Float	None	00	50
Nature of L3 load (Resistive=1, inductive=2, capacitive=3, Non Load=4)	4	Float	None	00	52

Nature of the system load(Resistive=1, inductive=2, capacitive =3, Non Load=4)	4	Float	None	00	54
Phase 1 voltage THD (2).	4	Float	%	00	7C
Phase 2 voltage THD (2).	4	Float	%	00	7E
Phase 3 voltage THD (2).	4	Float	%	00	80
Phase 1 current THD	4	Float	%	00	82
Phase 2 current THD	4	Float	%	00	84
Phase 3 current THD	4	Float	%	00	86
Average voltage THD (2).	4	Float	%	00	88
Average line current THD.	4	Float	%	00	8A
Total system active power demand (3).	4	Float	W	00	8C
Total system reactive power demand (3).	4	Float	var	00	8E
Total system apparent power demand.	4	Float	VA	00	90
Phase 1 current demand.	4	Float	A	00	92
Phase 2 current demand.	4	Float	A	00	94
Phase 3 current demand.	4	Float	A	00	96
Neutral current demand.	4	Float	A	00	98
Import active power demand	4	Float	W	00	9A
Export active power demand	4	Float	W	00	9C
Maximum total system active power demand (3).	4	Float	W	00	A2
Maximum total system reactive power demand (3).	4	Float	var	00	A4
Maximum total system apparent power demand.	4	Float	VA	00	A6
Maximum phase 1 current demand.	4	Float	A	00	A8
Maximum phase 2 current demand.	4	Float	A	00	AA
Maximum phase 3 current demand.	4	Float	A	00	AC
Maximum neutral current demand.	4	Float	A	00	AE
Maximum import active power demand	4	Float	W	00	B0
Maximum export active power demand	4	Float	W	00	B2
Total import active energy.	4	Float	kWh	05	00
Total export active energy.	4	Float	kWh	05	02
Total active Energy.	4	Float	kWh	05	04
Total import reactive energy.	4	Float	kvarh	05	08
Total export reactive energy.	4	Float	kvarh	05	0A
Total reactive Energy.	4	Float	kvarh	05	0C
Total apparent energy.	4	Float	kVAh	05	10
L1 import active Energy	4	Float	kWh	05	14
L2 import active Energy	4	Float	kWh	05	16
L3 import active Energy	4	Float	kWh	05	18
L1 export active Energy	4	Float	kWh	05	1A
L2 export active Energy	4	Float	kWh	05	1C
L3 export active Energy	4	Float	kWh	05	1E
L1 total active Energy	4	Float	kWh	05	20
L2 total active Energy	4	Float	kWh	05	22
L3 total active Energy	4	Float	kWh	05	24
L1 import reactive energy	4	Float	kvarh	05	26

L2 import reactive energy	4	Float	kvarh	05	28
L3 import reactive energy	4	Float	kvarh	05	2A
L1 export reactive energy	4	Float	kvarh	05	2C
L2 export reactive energy	4	Float	kvarh	05	2E
L3 export reactive energy	4	Float	kvarh	05	30
L1 total reactive energy	4	Float	kvarh	05	32
L2 total reactive energy	4	Float	kvarh	05	34
L3 total reactive energy	4	Float	kvarh	05	36
Total active energy of rate 1	4	Float	kWh	05	38
Total active energy of rate 2	4	Float	kWh	05	3A
Total active energy of rate 3	4	Float	kWh	05	3C
Total active energy of rate 4	4	Float	kWh	05	3E
Import active energy of rate 1	4	Float	kWh	05	40
Import active energy of rate 2	4	Float	kWh	05	42
Import active energy of rate 3	4	Float	kWh	05	44
Import active energy of rate 4	4	Float	kWh	05	46
Export active energy of rate 1	4	Float	kWh	05	48
Export active energy of rate 2	4	Float	kWh	05	4A
Export active energy of rate 3	4	Float	kWh	05	4C
Export active energy of rate 4	4	Float	kWh	05	4E
Total reactive energy of rate 1	4	Float	kvarh	05	50
Total reactive energy of rate 2	4	Float	kvarh	05	52
Total reactive energy of rate 3	4	Float	kvarh	05	54
Total reactive energy of rate 4	4	Float	kvarh	05	56
Import reactive energy of rate 1	4	Float	kvarh	05	58
Import reactive energy of rate 2	4	Float	kvarh	05	5A
Import reactive energy of rate 3	4	Float	kvarh	05	5C
Import reactive energy of rate 4	4	Float	kvarh	05	5E
Export reactive energy of rate 1	4	Float	kvarh	05	60
Export reactive energy of rate 2	4	Float	kvarh	05	62
Export reactive energy of rate 3	4	Float	kvarh	05	64
Export reactive energy of rate 4	4	Float	kvarh	05	66
Monthly energy consumption for the last 12 months					
Total active energy category (Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The total active energy consumption of the current months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	0C
The total active energy consumption of the last 1 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	16
The total active energy consumption of the last 2 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	20
The total active energy consumption of the last 3 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	2A
The total active energy consumption of the last 4 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	34

The total active energy consumption of the last 5 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	3E
The total active energy consumption of the last 6 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	48
The total active energy consumption of the last 7 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	52
The total active energy consumption of the last 8 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	5C
The total active energy consumption of the last 9 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	66
The total active energy consumption of the last 10 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	70
The total active energy consumption of the last 11 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	7A
The total active energy consumption of the last 12 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	84
Import active energy category (Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The import active energy consumption of the current months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	8E
The import active energy consumption of the last 1 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	98
The import active energy consumption of the last 2 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	A2
The import active energy consumption of the last 3 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	AC
The import active energy consumption of the last 4 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	B6
The import active energy consumption of the last 5 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	C0
The import active energy consumption of the last 6 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	CA
The import active energy consumption of the last 7 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	D4
The import active energy consumption of the last 8 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	DE
The import active energy consumption of the last 9 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	E8
The import active energy consumption of the last 10 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	F2
The import active energy consumption of the last 11 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0A	FC
The import active energy consumption of the last 12 months (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0B	06
Export active energy category					

(Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The export active energy consumption of the current months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	10
The export active energy consumption of the last 1 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	1A
The export active energy consumption of the last 2 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	24
The export active energy consumption of the last 3 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	2E
The export active energy consumption of the last 4 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	38
The export active energy consumption of the last 5 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	42
The export active energy consumption of the last 6 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	4C
The export active energy consumption of the last 7 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	56
The export active energy consumption of the last 8 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	60
The export active energy consumption of the last 9 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	6A
The export active energy consumption of the last 10 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	74
The export active energy consumption of the last 11 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	7E
The export active energy consumption of the last 12 months (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0B	88
Daily energy consumption for the last 31 days					
Total active energy category					
(Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The total active energy consumption of the current days (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0D	18
The total active energy consumption of the last 1 days (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0D	22
The total active energy consumption of the last 2 days (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0D	2C
The total active energy consumption of the last 3 days (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0D	36
The total active energy consumption of the last 4 days (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0D	40
The total active energy consumption of the last 5 days (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0D	4A
The total active energy consumption of the last 6 days (Total, Rate1, Rate2, Rate3, Rate4)	20	Float	kWh	0D	54

The total active energy consumption of the last 7 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	5E
The total active energy consumption of the last 8 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	68
The total active energy consumption of the last 9 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	72
The total active energy consumption of the last 10 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	7C
The total active energy consumption of the last 11 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	86
The total active energy consumption of the last 12 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	90
The total active energy consumption of the last 13 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	9A
The total active energy consumption of the last 14 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	A4
The total active energy consumption of the last 15 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	AE
The total active energy consumption of the last 16 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	B8
The total active energy consumption of the last 17 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	C2
The total active energy consumption of the last 18 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	CC
The total active energy consumption of the last 19 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	D6
The total active energy consumption of the last 20 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	E0
The total active energy consumption of the last 21 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	EA
The total active energy consumption of the last 22 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	F4
The total active energy consumption of the last 23 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0D	FE
The total active energy consumption of the last 24 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	08
The total active energy consumption of the last 25 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	12
The total active energy consumption of the last 26 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	1C
The total active energy consumption of the last 27 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	26
The total active energy consumption of the last 28 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	30
The total active energy consumption of the last 29 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	3A

The total active energy consumption of the last 30 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	44
The total active energy consumption of the last 31 days (Total、Rate1、Rate2、Rate3、Rate4)	20	Float	kWh	0E	4E

Notes:

1. The power factor has its sign adjusted to indicate the direction of the current. Positive refers to forward current, negative refers to reverse current.
2. In 3P3W mode, L1 represents the line voltage THD of L1-2, L2 represents the line voltage harmonic content of L2-3, and L3 represents the Line voltage THD of L3-1. In 3P4W, 1P2W, 1P3W and other modes, L1, L2 and L3 respectively represent the corresponding phase voltage harmonic content.
3. The power sum demand calculation is for import – export.

Measuring class parameter [Integer format data]

Holding Register Parameter [Read : Function code : 03H]				Register Address [Hex]	
Description	Length (bytes)	Data Format	Units	High Byte	Low Byte
Phase 1 line to neutral volts.	4	ULONG	0.01V	00	00
Phase 2 line to neutral volts.	4	ULONG	0.01V	00	02
Phase 3 line to neutral volts.	4	ULONG	0.01V	00	04
Phase 1 current.	4	ULONG	0.001A	00	06
Phase 2 current.	4	ULONG	0.001A	00	08
Phase 3 current.	4	ULONG	0.001A	00	0A
Phase 1 active power.	4	LONG	0.001kW	00	0C
Phase 2 active power.	4	LONG	0.001kW	00	0E
Phase 3 active power.	4	LONG	0.001kW	00	10
Phase 1 reactive power.	4	LONG	0.001kvar	00	12
Phase 2 reactive power.	4	LONG	0.001kvar	00	14
Phase 3 reactive power.	4	LONG	0.001kvar	00	16
Phase 1 apparent power.	4	ULONG	0.001kVA	00	18
Phase 2 apparent power.	4	ULONG	0.001kVA	00	1A
Phase 3 apparent power.	4	ULONG	0.001kVA	00	1C
Phase 1 power factor (1).	2	INT	0.001	00	1E
Phase 2 power factor (1).	2	INT	0.001	00	1F
Phase 3 power factor (1).	2	INT	0.001	00	20
Phase 1 phase angle.	2	INT	0.01°	00	21
Phase 2 phase angle.	2	INT	0.01°	00	22
Phase 3 phase angle.	2	INT	0.01°	00	23
Line 1 to Line 2 volts.	4	ULONG	0.01V	00	24
Line 2 to Line 3 volts.	4	ULONG	0.01V	00	26
Line 3 to Line 1 volts.	4	ULONG	0.01V	00	28
Frequency of supply voltages.	2	UINT	0.01Hz	00	2A
Total system active power.	4	LONG	0.001kW	00	2C
Total system reactive power.	4	LONG	0.001kvar	00	2E
Total system apparent power.	4	ULONG	0.001kVA	00	30
Total system power factor (1).	2	INT	0.001	00	32
Total system phase angle.	2	INT	0.01°	00	33
Sum of line currents.	4	ULONG	0.001A	00	34
Average line to neutral volts.	4	ULONG	0.01V	00	36
Average line to line volts.	4	ULONG	0.01V	00	38
Average line current.	4	ULONG	0.001A	00	3A
Neutral current.	4	ULONG	0.001A	00	3C
Nature of L1 load (Resistive=1, inductive=2, capacitive=3, Non Load=4)	2	UINT	None	00	46
Nature of L2 load (Resistive=1, inductive=2, capacitive=3, Non Load=4)	2	UINT	None	00	47
Nature of L3 load (Resistive=1, inductive=2, capacitive=3, Non Load=4)	2	UINT	None	00	48

Nature of the system load(Resistive=1, inductive=2, capacitive =3, Non Load=4)	2	UINT	None	00	49
Phase 1 voltage THD (2).	2	UINT	0.01%	00	5D
Phase 2 voltage THD (2).	2	UINT	0.01%	00	5E
Phase 3 voltage THD (2).	2	UINT	0.01%	00	5F
Phase 1 current THD	2	UINT	0.01%	00	60
Phase 2 current THD	2	UINT	0.01%	00	61
Phase 3 current THD	2	UINT	0.01%	00	62
Average voltage THD (2).	2	UINT	0.01%	00	63
Average line current THD.	2	UINT	0.01%	00	64
Total system active power demand (3).	4	LONG	0.001kW	00	66
Total system reactive power demand (3).	4	LONG	0.001kvar	00	68
Total system apparent power demand.	4	ULONG	0.001kVA	00	6A
Phase 1 current demand.	4	ULONG	0.001A	00	6C
Phase 2 current demand.	4	ULONG	0.001A	00	6E
Phase 3 current demand.	4	ULONG	0.001A	00	70
Neutral current demand.	4	ULONG	0.001A	00	72
Import active power demand	4	ULONG	0.001kW	00	74
Export active power demand	4	ULONG	0.001kW	00	76
Maximum total system active power demand (3).	4	LONG	0.001kW	00	7C
Maximum total system reactive power demand (3).	4	LONG	0.001kvar	00	7E
Maximum total system apparent power demand.	4	ULONG	0.001kVA	00	80
Maximum phase 1 current demand.	4	ULONG	0.001A	00	82
Maximum phase 2 current demand.	4	ULONG	0.001A	00	84
Maximum phase 3 current demand.	4	ULONG	0.001A	00	86
Maximum neutral current demand.	4	ULONG	0.001A	00	88
Maximum import active power demand	4	ULONG	0.001kW	00	8A
Maximum export active power demand	4	ULONG	0.001kW	00	8C
Total import active energy.	4	ULONG	0.01kWh	04	00
Total export active energy.	4	ULONG	0.01kWh	04	02
Total active Energy.	4	LONG	0.01kWh	04	04
Total import reactive energy.	4	ULONG	0.01kvarh	04	08
Total export reactive energy.	4	ULONG	0.01kvarh	04	0A
Total reactive Energy.	4	LONG	0.01kvarh	04	0C
Total apparent energy.	4	ULONG	0.01kVA	04	10
L1 import active Energy	4	ULONG	0.01kWh	04	14
L2 import active Energy	4	ULONG	0.01kWh	04	16
L3 import active Energy	4	ULONG	0.01kWh	04	18
L1 export active Energy	4	ULONG	0.01kWh	04	1A
L2 export active Energy	4	ULONG	0.01kWh	04	1C
L3 export active Energy	4	ULONG	0.01kWh	04	1E
L1 total active Energy	4	LONG	0.01kWh	04	20
L2 total active Energy	4	LONG	0.01kWh	04	22
L3 total active Energy	4	LONG	0.01kWh	04	24
L1 import reactive energy	4	ULONG	0.01kvarh	04	26

L2 import reactive energy	4	ULONG	0.01kvarh	04	28
L3 import reactive energy	4	ULONG	0.01kvarh	04	2A
L1 export reactive energy	4	ULONG	0.01kvarh	04	2C
L2 export reactive energy	4	ULONG	0.01kvarh	04	2E
L3 export reactive energy	4	ULONG	0.01kvarh	04	30
L1 total reactive energy	4	LONG	0.01kvarh	04	32
L2 total reactive energy	4	LONG	0.01kvarh	04	34
L3 total reactive energy	4	LONG	0.01kvarh	04	36
Total active energy of rate 1	4	LONG	0.01kWh	04	38
Total active energy of rate 2	4	LONG	0.01kWh	04	3A
Total active energy of rate 3	4	LONG	0.01kWh	04	3C
Total active energy of rate 4	4	LONG	0.01kWh	04	3E
Import active energy of rate 1	4	ULONG	0.01kWh	04	40
Import active energy of rate 2	4	ULONG	0.01kWh	04	42
Import active energy of rate 3	4	ULONG	0.01kWh	04	44
Import active energy of rate 4	4	ULONG	0.01kWh	04	46
Export active energy of rate 1	4	ULONG	0.01kWh	04	48
Export active energy of rate 2	4	ULONG	0.01kWh	04	4A
Export active energy of rate 3	4	ULONG	0.01kWh	04	4C
Export active energy of rate 4	4	ULONG	0.01kWh	04	4E
Total reactive energy of rate 1	4	LONG	0.01kvarh	04	50
Total reactive energy of rate 2	4	LONG	0.01kvarh	04	52
Total reactive energy of rate 3	4	LONG	0.01kvarh	04	54
Total reactive energy of rate 4	4	LONG	0.01kvarh	04	56
Import reactive energy of rate 1	4	ULONG	0.01kvarh	04	58
Import reactive energy of rate 2	4	ULONG	0.01kvarh	04	5A
Import reactive energy of rate 3	4	ULONG	0.01kvarh	04	5C
Import reactive energy of rate 4	4	ULONG	0.01kvarh	04	5E
Export reactive energy of rate 1	4	ULONG	0.01kvarh	04	60
Export reactive energy of rate 2	4	ULONG	0.01kvarh	04	62
Export reactive energy of rate 3	4	ULONG	0.01kvarh	04	64
Export reactive energy of rate 4	4	ULONG	0.01kvarh	04	66
Monthly energy consumption for the last 12 months					
Total active energy category					
(Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The total active energy consumption of the current months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	0C
The total active energy consumption of the last 1 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	16
The total active energy consumption of the last 2 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	20
The total active energy consumption of the last 3 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	2A
The total active energy consumption of the last 4 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	34

The total active energy consumption of the last 5 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	3E
The total active energy consumption of the last 6 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	48
The total active energy consumption of the last 7 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	52
The total active energy consumption of the last 8 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	5C
The total active energy consumption of the last 9 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	66
The total active energy consumption of the last 10 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	70
The total active energy consumption of the last 11 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	7A
The total active energy consumption of the last 12 months (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	09	84
Import active energy category (Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The import active energy consumption of the current months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	8E
The import active energy consumption of the last 1 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	98
The import active energy consumption of the last 2 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	A2
The import active energy consumption of the last 3 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	AC
The import active energy consumption of the last 4 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	B6
The import active energy consumption of the last 5 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	C0
The import active energy consumption of the last 6 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	CA
The import active energy consumption of the last 7 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	D4
The import active energy consumption of the last 8 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	DE
The import active energy consumption of the last 9 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	E8
The import active energy consumption of the last 10 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	F2
The import active energy consumption of the last 11 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	09	FC
The import active energy consumption of the last 12 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	06
Export active energy category					

(Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The export active energy consumption of the current months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	10
The export active energy consumption of the last 1 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	1A
The export active energy consumption of the last 2 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	24
The export active energy consumption of the last 3 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	2E
The export active energy consumption of the last 4 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	38
The export active energy consumption of the last 5 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	42
The export active energy consumption of the last 6 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	4C
The export active energy consumption of the last 7 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	56
The export active energy consumption of the last 8 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	60
The export active energy consumption of the last 9 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	6A
The export active energy consumption of the last 10 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	74
The export active energy consumption of the last 11 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	7E
The export active energy consumption of the last 12 months (Total、Rate1、Rate2、Rate3、Rate4)	20	ULONG	0.01kWh	0A	88
Daily energy consumption for the last 31 days					
Total active energy category					
(Each set of data includes the energy of all rate segments, the energy of rate 1, the energy of rate 2, the energy of rate 3 and the energy of rate 4 respectively)					
The total active energy consumption of the current days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	18
The total active energy consumption of the last 1 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	22
The total active energy consumption of the last 2 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	2C
The total active energy consumption of the last 3 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	36
The total active energy consumption of the last 4 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	40
The total active energy consumption of the last 5 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	4A
The total active energy consumption of the last 6 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	54

The total active energy consumption of the last 7 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	5E
The total active energy consumption of the last 8 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	68
The total active energy consumption of the last 9 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	72
The total active energy consumption of the last 10 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	7C
The total active energy consumption of the last 11 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	86
The total active energy consumption of the last 12 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	90
The total active energy consumption of the last 13 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	9A
The total active energy consumption of the last 14 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	A4
The total active energy consumption of the last 15 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	AE
The total active energy consumption of the last 16 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	B8
The total active energy consumption of the last 17 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	C2
The total active energy consumption of the last 18 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	CC
The total active energy consumption of the last 19 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	D6
The total active energy consumption of the last 20 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	E0
The total active energy consumption of the last 21 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	EA
The total active energy consumption of the last 22 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	F4
The total active energy consumption of the last 23 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0C	FE
The total active energy consumption of the last 24 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	08
The total active energy consumption of the last 25 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	12
The total active energy consumption of the last 26 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	1C
The total active energy consumption of the last 27 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	26
The total active energy consumption of the last 28 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	30
The total active energy consumption of the last 29 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	3A

The total active energy consumption of the last 30 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	44
The total active energy consumption of the last 31 days (Total、Rate1、Rate2、Rate3、Rate4)	20	LONG	0.01kWh	0D	4E
64-bit integer energy register					
Total import active energy.	8	INT64	Wh	1D	00
Total export active energy.	8	INT64	Wh	1D	04
Total active Energy (Import + Export).	8	INT64	Wh	1D	08
Total import reactive energy.	8	INT64	varh	1D	10
Total export reactive energy.	8	INT64	varh	1D	14
Total reactive energy (Import + Export).	8	INT64	varh	1D	18
Total apparent energy.	8	INT64	VAh	1D	20
L1 import active Energy	8	INT64	Wh	1D	24
L2 import active Energy	8	INT64	Wh	1D	28
L3 import active Energy	8	INT64	Wh	1D	2C
L1 export active Energy	8	INT64	Wh	1D	30
L2 export active Energy	8	INT64	Wh	1D	34
L3 export active Energy	8	INT64	Wh	1D	38
L1 total active Energy	8	INT64	Wh	1D	3C
L2 total active Energy	8	INT64	Wh	1D	40
L3 total active Energy	8	INT64	Wh	1D	44
L1 import reactive energy	8	INT64	varh	1D	48
L2 import reactive energy	8	INT64	varh	1D	4C
L3 import reactive energy	8	INT64	varh	1D	50
L1 export reactive energy	8	INT64	varh	1D	54
L2 export reactive energy	8	INT64	varh	1D	58
L3 export reactive energy	8	INT64	varh	1D	5C
L1 total reactive energy	8	INT64	varh	1D	60
L2 total reactive energy	8	INT64	varh	1D	64
L3 total reactive energy	8	INT64	varh	1D	68
Total active energy Rate 1	8	INT64	Wh	1D	6C
Total active energy Rate 2	8	INT64	Wh	1D	70
Total active energy Rate 3	8	INT64	Wh	1D	74
Total active energy Rate 4	8	INT64	Wh	1D	78
Import active energy Rate 1	8	INT64	Wh	1D	7C
Import active energy Rate 2	8	INT64	Wh	1D	80
Import active energy Rate 3	8	INT64	Wh	1D	84
Import active energy Rate 4	8	INT64	Wh	1D	88
Export active energy Rate 1	8	INT64	Wh	1D	8C
Export active energy Rate 2	8	INT64	Wh	1D	90
Export active energy Rate 3	8	INT64	Wh	1D	94
Export active energy Rate 4	8	INT64	Wh	1D	98
Total reactive energy Rate 1	8	INT64	varh	1D	9C
Total reactive energy Rate 2	8	INT64	varh	1D	A0
Total reactive energy Rate 3	8	INT64	varh	1D	A4

Total reactive energy Rate 4	8	INT64	varh	1D	A8
Import reactive energy Rate 1	8	INT64	varh	1D	AC
Import reactive energy Rate 2	8	INT64	varh	1D	B0
Import reactive energy Rate 3	8	INT64	varh	1D	B4
Import reactive energy Rate 4	8	INT64	varh	1D	B8
Export reactive energy Rate 1	8	INT64	varh	1D	BC
Export reactive energy Rate 2	8	INT64	varh	1D	C0
Export reactive energy Rate 3	8	INT64	varh	1D	C4
Export reactive energy Rate 4	8	INT64	varh	1D	C8

Notes:

1. The power factor has its sign adjusted to indicate the direction of the current. Positive refers to forward current, negative refers to reverse current.
2. In 3P3W mode, L1 represents the line voltage THD of L1-2, L2 represents the line voltage harmonic content of L2-3, and L3 represents the Line voltage THD of L3-1. In 3P4W, 1P2W, 1P3W and other modes, L1, L2 and L3 respectively represent the corresponding phase voltage harmonic content.
3. The power sum demand calculation is for import – export.

Set class parameters

Holding Register Parameter [Read : Function code : 03H ; Write : Function code : 10H]				Register Address [Hex]		
Parameter	Description	Length (bytes)	Data Format	High Byte	Low Byte	Mode
Key Parameter Programming Authorization (KPPA)	Read: to get the status of the KPPA 0 = not authorized; 1 = authorized Write the correct password to get KPPA, enable to program key parameters.	2	UINT	50	00	R/W
System Type	Write system type: 1 = 1P2W; 2 = 3P3W; 3 = 3P4W,(default); 4 = 1P3W; (KPPA is asked)	2	UINT	50	01	R/W
Demand Period	Write demand period: 0~60 minutes, Default 60. Range: 0~60, 0 means function update every second.	2	UINT	50	02	R/W
Slide time	Default 1, min. Range: 1 ~ (Demand Period -1).	2	UINT	50	03	R/W
Modbus address	Write the modbus address Range: 1 to 247 for MODBUS Protocol, default 1.	2	UINT	50	05	R/W
Network Baud Rate	Write the network port baud rate for MODBUS Protocol, where: 0 = 1200 baud. 1 = 2400 baud. 2 = 4800 baud. 3 = 9600 baud, default. 4 = 19200 baud. 5 = 38400 baud.	2	UINT	50	06	R/W
Parity and stop bit	Write the network port parity/stop bits for MODBUS Protocol, where: 0 = One stop bit and no parity, default. 1 = One stop bit and even parity. 2 = One stop bit and odd parity. 3 = Two stop bits and no parity.	2	UINT	50	07	R/W
Password	Read: to get the password of the meter Write: to program the new password of the meter Default : 0000 (KPPA is asked)	2	UINT	50	08	R/W
Pulse 1 Energy Type	Write MODBUS Protocol input parameter for pulse output 1:	2	UINT	50	09	R/W

	1: import active energy 2: total active energy 4: export active energy, default 5: import reactive energy 6: total reactive energy 8: export reactive energy					
Pulse 1 Rate	Write pulse rate index: n = 0 to 5 0 : 0.001 kwh/imp 1 : 0.01 kwh/imp, default 2 : 0.1 kwh/imp 3 : 1 kwh/imp 4 : 10 kwh/imp 5 : 100 kwh/imp	2	UINT	50	0A	R/W
Pulse 1 Width	Write pulse on period in milliseconds: 60, 100 or 200, default 100.	2	UINT	50	0B	R/W
Current Direction correction (when the external CT is connected reversely)	0 = L1 Frd, L2 Frd, L3 Frd 1 = L1 Rev, L2 Frd, L3 Frd 2 = L1 Frd, L2 Rev, L3 Frd 3 = L1 Rev, L2 Rev, L3 Frd 4 = L1 Frd, L2 Frd, L3 Rev 5 = L1 Rev, L2 Frd, L3 Rev 6 = L1 Frd, L2 Rev, L3 Rev 7 = L1 Rev, L2 Rev, L3 Rev Default 0 (KPPA is asked)	2	UINT	50	0F	R/W
PT1	PT1 Range 30 - 500000V, Default 230 (KPPA is asked)	4	ULONG	50	12	R/W
PT2	PT2 Range 30- 500V, Default 230 (KPPA is asked)	2	UINT	50	14	R/W
CT1	CT1 Range 1-9999A, Default 5, (KPPA is asked)	2	UINT	50	15	R/W
CT2	CT2 Range: 1A or 5A , Default 5A (KPPA is asked)	2	UINT	50	16	R/W
Automatic Scroll Display Time	Automatic scroll display time, unit : second Range 0~60, default : 0 Note: 0 mean stop automatic scroll display	2	UINT	50	18	R/W
Backlit time	Backlit time, unit : minute. Default 60. Range 0~120 or 255, 0 means backlit always on, 255 means backlit always off.	2	UINT	50	19	R/W
System time	Data definition: 20-Year-Month-Date-Week-Hour- Minute-Second	8	BCD	50	1A	R/W
Tariff	Data definition:	24	BCD	50	1E	R/W

	Tariff number-Min-Hour Tariff number: 00, 01, 02, 03, 04; 00 mean invalid tariff number Min: 00-59 Hour: 00-23					
Running time (Data in units of minutes)	Running time. Unit : minute. Write 0 to reset the running time with load. No response if write other value. Note: The meter starts timing when it's powered on	4	ULONG	50	3C	R/W
Running time with load (Data in units of minutes)	Running time with load. Unit : minute. Write 0 to reset the running time with load. No response if write other value. Note: The meter starts timing when power greater than 0 detected	4	ULONG	50	3E	R/W
Reset historical data	0 = reset max. demand 8 = reset daily energy consumption 9 = reset monthly energy consumption (KPPA is asked)	2	UINT	56	00	W
Meter code	The code of the meter	2	HEX	56	01	R
Serial number	The serial number of the meter	4	ULONG	56	02	R
Software version number	Software version number : XX.YY Data definition : The first byte represents XX, and the second byte represents YY	2	HEX	56	04	R
Hardware version number	Hardware version number : XX.YY Data definition : The first byte represents XX, and the second byte represents YY	2	HEX	56	05	R
version number of displayed	version number of displayed : XX.YY Data definition : The first byte represents XX, and the second byte represents YY	2	HEX	56	06	R
Fault code	Fault code 0 mean No fault. 1 mean Battery low voltage fault.	2	HEX	56	07	R

(1). Example for setting the tariff segment:

Example A: Setting T1 = 00:00 to 03:00, T2 = 03:00 to 06:00, T3 = 06:00 to 08:00, T4 = 08:00 to 00:00,

Send the following command (Hex):

01 10 50 1E 00 0C 18 01 00 00 02 00 03 03 00 06 04 00 08 00 00 00 00 00 00 00 00 00 00 00 00 F6 2D

Among them, red character **01** represents the Modbus communication address of the meter, and **50 1E** represents the register address of the tariff. The red character **F6 2D** is the CRC check code.

01 00 00 represents the start time of T1,

02 00 03 represents the start time of T2,

03 00 06 represents the start time of T3,

04 00 08 represents the start time of T4.

If the remaining four time points are not used, write them all to 00 00 00

Example B: Setting T1 = 00:00 to 03:00 and 12:00 to 14:00; T2 = 03:00 to 06:00 and 14:00 to 16:00; T3 = 06:00 to 08:00 and

16:00 to 18:00; T4 = 08:00 to 12:00 and 18:00 to 00:00

Send the following command (Hex):

01 10 50 1E 00 0C 18 01 00 00 02 00 03 03 00 06 04 00 08 01 00 12 02 00 14 03 00 16 04 00 18 A3 60

Among them, red character **01** represents the Modbus communication address of the meter, and **50 1E** represents the register address of the tariff. The red character **A3 60** is the CRC check code.

01 00 00, 01 00 12 represents the start time of T1,

02 00 03, 02 00 14 represents the start time of T2,

03 00 06, 03 00 16 represents the start time of T3,

04 00 08, 04 00 18 represents the start time of T4.

Example:

1, Read Input Registers

Example: Read "Phase 1 line to neutral volts"

Request: 01 04 00 00 00 02 71 CB

Where, 01 = Meter address

04 = Function code

00 = High byte of registers starting address

00 = Low byte of registers starting address

00 = High byte of registers number

02 = Low byte of registers number

71 = CRC Low

CB = CRC High

Response: 01 04 04 43 66 33 34 1B 38

Where, 01 = Meter address

04 = Function code

04 = Byte count

43 = Data, (High Word, High Byte)

66 = Data, (High Word, Low Byte)

33 = Data, (Low Word, High Byte)

34 = Data, (Low Word, Low Byte)

1B = CRC Low

38 = CRC High

Note: 43 66 33 34(Hex) = 230.2 (Floating point)

Example: Read "Phase 1 line to neutral volts" (ULONG Format)

Request: 01 03 00 00 00 02 C4 B0

Where, 01 = Meter address

03 = Function code

00 = High byte of registers starting address

00 = Low byte of registers starting address

00 = High byte of registers number

02 = Low byte of registers number

C4 = CRC Low

B0 = CRC High

Response: 01 03 04 00 00 61 AA 53 DC

Where, 01 = Meter address

04 = Function code

04 = Byte count

00 = Data, (High Word, High Byte)

00 = Data, (High Word, Low Byte)

61 = Data, (Low Word, High Byte)

AA = Data, (Low Word, Low Byte)

53 = CRC Low

DC = CRC High

Note: 00 00 61 AA(Hex) = 25002(ULONG) * 0.01V = 250.02V

2, Read Holding Registers

Example: Read "Slide time"

Request: 01 03 50 03 00 01 65 0A

Where, 01 = Meter address

03 = Function code

50 = High byte of registers starting address

03 = Low byte of registers starting address

00 = High byte of registers number

01 = Low byte of registers number

65 = CRC Low

0A = CRC High

Response: 01 03 02 00 05 78 47

Where, 01 = Meter address

03 = Function code

04 = Byte Count

00 = Data, (High Byte)

05 = Data, (Low Byte)

78 = CRC Low

47 = CRC High

Note: 00 05 (Hex) = 5 (UINT)

3, Write Holding Registers

Example: Write "Demand Period" = 30

Request: 01 10 50 02 00 01 02 00 1E 77 BF

Where, 01 = Meter address

10 = Function code

50 = High byte of registers starting address

02 = Low byte of registers starting address

00 = High byte of registers number

01 = Low byte of registers number

02 = Byte Count

00 = Data, (High Byte)

1E = Data, (Low Byte)

77 = CRC Low

BF = CRC High

Note: 00 1E (Hex) = 30(UINT)

Response: 01 10 50 02 00 01 B1 09

Where, 01 = Meter address

10 = Function code

50 = High byte of registers starting address

02 = Low byte of registers starting address

00 = High byte of registers number

01 = Low byte of registers number

B1 = CRC Low

09 = CRC High